COMMON CHARACTERISTICS

PROGRAMMING MODEL



INSTRUCTION SET – OP CODES, Execution Time, Memory Requirements

INSTRUCTIONS		IMMEDIATE			ABSOLUTE			ZERO PAGE			ACCUM.			IMPLIED			(IND,X)			(IND),Y			Z,PAGE,X			ABS,X			ABS,Y			RELATIVE			INDIRECT			Z,PAGE,Y			CONDITION CODES						
MNEMONIC	OPERATION	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	N	Z	C	I	D	V
ADC	A+M+C → A (4) (1)	69	2	2	6D	4	3	65	3	2							61	6	2	71	5	2	75	4	2	7D	4	3	79	4	3										✓	✓	✓	–	–	✓
AND	A∧M→A (1)	29	2	2	2D	4	3	25	3	2							21	6	2	31	5	2	35	4	2	3D	4	3	39	4	3										✓	✓	–	–	–	–
ASL	C 7 … 0 ← 0				0E	6	3	06	5	2	0A	2	1										16	6	2	1E	7	3													✓	✓	✓	–	–	–
BCC	BRANCH ON C=0 (2)																															90	2	2							–	–	–	–	–	–
BCS	BRANCH ON C=1 (2)																															B0	2	2							–	–	–	–	–	–
BEQ	BRANCH ON Z=1 (2)																															F0	2	2							–	–	–	–	–	–
BIT	A∧M				2C	4	3	24	3	2																															M_7	✓	–	–	–	M_6
BMI	BRANCH ON N=1 (2)																															30	2	2							–	–	–	–	–	–
BNE	BRANCH ON Z=0 (2)																															D0	2	2							–	–	–	–	–	–
BPL	BRANCH ON N=0 (2)																															10	2	2							–	–	–	–	–	–
BRK	(See Fig. 1)													00	7	1																									–	–	–	1	–	–
BVC	BRANCH ON V=0 (2)																															50	2	2							–	–	–	–	–	–
BVS	BRANCH ON V=1 (2)																															70	2	2							–	–	–	–	–	–
CLC	0 → C													18	2	1																									–	–	0	–	–	–
CLD	0 → D													D8	2	1																									–	–	–	–	0	–
CLI	0 → I													58	2	1																									–	–	–	0	–	–
CLV	0 → V													B8	2	1																									–	–	–	–	–	0
CMP	A–M (1)	C9	2	2	CD	4	3	C5	3	2							C1	6	2	D1	5	2	D5	4	2	DD	4	3	D9	4	3										✓	✓	✓	–	–	–
CPX	X–M	E0	2	2	EC	4	3	E4	3	2																															✓	✓	✓	–	–	–
CPY	Y–M	C0	2	2	CC	4	3	C4	3	2																															✓	✓	✓	–	–	–
DEC	M–1 → M				CE	6	3	C6	5	2													D6	6	2	DE	7	3													✓	✓	–	–	–	–
DEX	X–1 → X													CA																											✓	✓	–	–	–	–
DEY	Y–1 → Y													88																											✓	✓	–	–	–	–
EOR	A ⊻ M → A (1)	49	2	2	4D	4	3	45	3	2							41	6	2	51	5	2	55	4	2	5D	4	3	59	4	3										✓	✓	–	–	–	–
INC	M+1 → M				EE	6	3	E6	5	2													F6	6	2	FE	7	3													✓	✓	–	–	–	–
INX	X+1 → X													E8	2	1																									✓	✓	–	–	–	–
INY	Y+1 → Y													C8	2	1																									✓	✓	–	–	–	–
JMP	JUMP TO NEW LOC.				4C	3	3																												6C	5	3				–	–	–	–	–	–
JSR	(See Fig. 2) JUMP SUB				20	6	3																																		–	–	–	–	–	–
LDA	M → A (1)	A9	2	2	AD	4	3	A5	3	2							A1	6	2	B1	5	2	B5	4	2	BD	4	3	B9	4	3										✓	✓	–	–	–	–

		IMMEDIATE			ABSOLUTE			ZERO PAGE			ACCUM.			IMPLIED			(IND,X)			(IND),Y			Z,PAGE,X			ABS,X			ABS,Y			RELATIVE			INDIRECT			Z,PAGE,Y			CONDITION CODES						
MNEMONIC	OPERATION	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	OP	N	#	N	Z	C	I	D	V
LDX	M → X (1)	A2	2	2	AE	4	3	A6	3	2																			BE	4	3										✓	✓	–	–	–	–
LDY	M → Y (1)	A0	2	2	AC	4	3	A4	3	2													B4	4	2	BC	4	3													✓	✓	–	–	–	–
LSR	0 → 7 … 0 → C				4E	6	3	46	5	2	4A	2	1										56	6	2	5E	7	3													0	✓	✓	–	–	–
NOP	NO OPERATION													EA	2	1																									–	–	–	–	–	–
ORA	A∨M → A	09	2	2	0D	4	3	05	3	2							01	6	2	11	5	2	15	4	2	1D	4	3	19	4	3										✓	✓	–	–	–	–
PHA	A → Ms S–1 → S													48	3	1																									–	–	–	–	–	–
PHP	P → Ms S–1 → S													08	3	1																									–	–	–	–	–	–
PLA	S+1 → S Ms → A													68	4	1																									✓	✓	–	–	–	–
PLP	S+1 → S Ms → P													28	4	1																									(RESTORED)					
ROL	7 … 0 ← C				2E	6	3	26	5	2	2A	2	1										36	6	2	3E	7	3													✓	✓	✓	–	–	–
ROR	C → 7 … 0				6E	6	3	66	5	2	6A	2	1										76	6	2	7E	7	3													✓	✓	✓	–	–	–
RTI	(See Fig. 1) RTRN INT													40	6	1																									(RESTORED)					
RTS	(See Fig. 2) RTRN SUB													60	6	1																									–	–	–	–	–	–
SBC	A–M–C → A (1)	E9	2	2	ED	4	3	E5	3	2							E1	6	2	F1	5	2	F5	4	2	FD	4	3	F9	4	3										✓	✓	(3)	–	–	✓
SEC	1 → C													38	2	1																									–	–	1	–	–	–
SED	1 → D													F8	2	1																									–	–	–	–	1	–
SEI	1 → I													78	2	1																									–	–	–	1	–	–
STA	A → M				8D	4	3	85	3	2							81	6	2	91	6	2	95	4	2	9D	5	3	99	5	3										–	–	–	–	–	–
STX	X → M				8E	4	3	86	3	2																															96	4	2	–	–	–	–	–	–
STY	Y → M				8C	4	3	84	3	2													94	4	2																	–	–	–	–	–	–
TAX	A → X													AA	2	1																									✓	✓	–	–	–	–
TAY	A → Y													A8	2	1																									✓	✓	–	–	–	–
TSX	S → X													BA	2	1																									✓	✓	–	–	–	–
TXA	X → A													8A	2	1																									✓	✓	–	–	–	–
TXS	X → S													9A	2	1																									–	–	–	–	–	–
TYA	Y → A													98	2	1																									✓	✓	–	–	–	–

(1) ADD 1 TO "N" IF PAGE BOUNDRY IS CROSSED

(2) ADD 1 TO "N" IF BRANCH OCCURS TO SAME PAGE.
ADD 2 TO "N" IF BRANCH OCCURS TO DIFFERENT PAGE.

(3) CARRY NOT = BORROW.

(4) IF IN DECIMAL MODE Z FLAG IS INVALID.
ACCUMULATOR MUST BE CHECKED FOR ZERO RESULT.

X INDEX . X
Y INDEX Y
A ACCUMULATOR
M MEMORY PER EFFECTIVE ADDRESS
Ms MEMORY PER STACK POINTER

\+ ADD
– SUBTRACT
∧ AND
∨ OR
⊻ EXCLUSIVE OR

✓ MODIFIED
– NOT MODIFIED
M_7 MEMORY BIT 7
M_6 MEMORY BIT 6

N NO. CYCLES
NO. BYTES